

Klemko Techniek B.V.
Phone: +31 (0)880023300
E-mail: info@klemko.nl

klemko®

876804.jpg

Leddriver constante stroom

Package type: CT á 1 pce

PRODUCT SPECIFICATIONS:

| | |
|---|-----------------|
| Protocol | Phase cut-off |
| Model | Static |
| Output power (W) | 4.2 - 8.4 |
| Housing | Plastic housing |
| Suitable for constant voltage | No |
| Output voltage (V) | 6 - 12 |
| Input voltage (V) | 198 - 264 |
| Suitable for DC-voltage (primary side) | No |
| Suitable for constant current | Yes |
| Output current (mA) | 700 - 700 |
| No | |
| Degree of protection (IP) | IP20 |
| Protection class | II |
| Suitable for outdoor use | No |
| Length (mm) | 58 |
| Width (mm) | 36 |
| Height (mm) | 20 |
| Rated frequency (Hz) | 50 - 60 |
| 0.9 | |
| Max. starting current (A) | 5 |
| Ambient temperature (°C) | -20 - +60 |
| White | |
| Yes | |
| Number of channels | 1 |
| 1 - 1 | |
| Frequency input voltage (Hz) | 50 - 60 |
| Independently operating | Yes |
| Yes | |
| Overload protection | Yes |
| Yes | |
| Overtemperature protection | Yes |
| Yes | |
| Yes | |
| Short-circuit protected | Yes |
| No | |
| Efficiency (%) | 72 |
| (kV) | 1 |
| (kV) | 0.5 |
| None | |
| Max. number of luminaires per miniature circuit breaker B16 | 224 |
| Max. number of luminaires per miniature | 266 |

| | |
|---|---------|
| circuit breaker C16 | |
| (h) | 50000 |
| Dimmable | Yes |
| Operation by Bluetooth | No |
| Dimming DALI-2 | No |
| IFTTT support available | No |
| Compatible with Google Assistant | No |
| Compatible with Amazon Alexa | No |
| Compatible with Casambi | No |
| Dimming potentiometer (integrated) | No |
| Compatible with Apple HomeKit | No |
| Suitable for pulse button | No |
| Dimming RF | No |
| Dimming manufacturer's proprietary system | No |
| Dimming 1-10 V | No |
| Dimming LineSwitch | No |
| Dimming phase cut-on | No |
| Dimming DALI | No |
| Dimming programmable | No |
| Dimming Sine Wave Reduction (%) | 8 - 100 |
| Dimming DMX | No |
| Constant light output (CLO) | No |
| Dimming Touch and Dim | No |
| Dimming DSI | No |
| Dimming Zigbee | No |
| Dimming phase cut-off | Yes |
| Dimming 0-10 V | No |
| Dimming with push-button | No |